

# PSCL series power supply

Switch mode power supply 12VDC, IP67


CODE: PSCL12030

EN/II

TYPE: PSCL 12V/3A switch mode power supply

## Features of the power supply unit:

- power output 3A/12VDC\*
- universal AC input voltage range 90÷264V
- high efficiency 83%
- standby power <0,3W
- efficiency level: V
- IP 67 case
- protections:
  - SCP short-circuit protection
  - overvoltage protection (AC input)
  - overload (OLP)
- warranty – 2 year from the production date




## DESCRIPTION

Stabilized DC power supply is intended for supply equipments that require stabilised voltage of **12V DC**. When connected to fuse blocks of the LB4/xx/xx family, the power supply unit can feed more equipments (max. 4). The power supply unit is protected against short-circuit, overload and overvoltage.

## SPECIFICATIONS.

Supply voltage	90 ÷ 264 V AC 50÷60Hz
Current consumption	0,37A@230VAC max.
Supply power	36W max.
Efficiency	83%
Output voltage	12V DC
Output current $t_{AMB} < 30^{\circ}\text{C}$	3 A - refer to graph 1.
Output current $t_{AMB} = 40^{\circ}\text{C}$	2,1 A - refer to graph 1.
Ripple voltage	100mV p-p max.
Short-circuit protection SCP	electronic, automatic recovery
Overload protection OLP	150-200% of power supply, automatic recovery
IP protection class	IP67
Operation conditions	temperature -10 °C÷40 °C relative humidity 20%...90% without condensation
Dimensions (LxWxH)	135 x 50 x33 [mm]
Net/gross weight	0,31kg / 0,34kg
Protection class EN 60950-1:2007	II (second)
Lenght of DC cable	0,5 m
Lenght of AC cable	0,3 m
Storage temperature	-20°C...+60°C

\* In order to extend the life of the power supply, the load current of 2,1A is recommended.



Graph 1.  
Relation between output current and ambient temperature (instantaneous load).





Fig.1 Dimension of power supply.

## ACCESORIES

ACCESORIES :  
[1] adapter CABLE - PLUG DC 5,5/2,1 - code ML109



For power supplies are available accessories - fuse blocks and cable adapter. For details –visit [www.pulsar.pl](http://www.pulsar.pl).

\* Refer to graph 1